

SES-X-FA2LRL01 2 CH Unbalanced RCA Line Level Audio over Fiber Extender



FEATURES

- 2-Channel RCA Audio over Single Fiber Transmission
- Simplex LC Fiber Connectors
- 24-Bit Digitally Encoded Analog Audio
- Transmission Distance: up to 12.4 miles over Singlemode Fiber and up to 984ft. via Multimode Fiber
- No Loss in Signal Quality
- Adjustment Free Plug & Play Operation
- Enable Cascaded Audio Setups
- Line Level Unbalanced Audio Operation
- Indicator LEDs Monitor Fiber Link and Power
- Housed in Rugged Aluminum Enclosures
- FCC & RoHS Compliant

SES-X-FA2LRT01 AUDIO FIBER EXTENDER

Set Up Instructions

1. Secure the units in a safe location, where they will not be subject to impact and where there is room around the unit so nothing will interfere with the fiber optic cabling causing it to bend sharply in a tight radius in any way that can severely affect the signal transfer.
2. Use proper cable management and handling for routing fiber optic cable.
3. Carefully connect your source(s) to the transmitter input(s) and the receiver unit output(s) to your receiving device input(s) using the RCA connectors on the transmitter and on the receiver unit.
4. CLEAN* the LC fiber optical cable contacts that will be used for connecting the Tx and Rx units and attach the fiber cable to the LC connections and secure.
5. Connect the included power supplies to the transmitter and receiver units, and plug them both into an AC power source (100-240VAC 50/60Hz).

* CLEAN: All fiber optical cable contacts require cleaning each time before inserting into a device's outputs or inputs. Failure to clean the contacts can damage the unit's optics over time and can also permanently damage the cable and the device.

Use cleaning kits designed specifically for fiber optics.

SPECIFICATIONS	
Unity Gain	0dB In, 0dB Out
Total Harmonic Distortion	<0.05%
Signal to Noise Ratio	> 90dB Ref. 4dBu, A Weighting
Maximum Balanced Input Signal	7dBu
Max Line Input/Output Voltage	5Vp-p
Optical Wavelength	1310nm
Frequency Response	20Hz—20KHz
Sample Rate	48KHz, 24K bit rate
Input Power	5VDC/1A
Input Impedance (Tx)	100k Ohms
Output Impedance (Rx)	10 Ohms
Unit Dimensions Each Unit	4.125 x 4.25/5.0 with fiber connectors x 1.25 in
Power Consumption	<1W
Includes	(2) 5VDC/1A Power Adapters, (2) LC Simplex SFPs 1310nm

SES-X-FA2LRT01 AUDIO FIBER EXTENDER

TRANSMITTER



- 1 LC Simplex Fiber Output
- 2 Right Analog Unbalanced Audio RCA Input
- 3 Left Analog Unbalanced Audio RCA input
- 4 5VDC / 1A 2.5mm DC Power Input Jack

RECEIVER



- 1 LC Simplex Fiber Input
- 2 Right Analog Unbalanced Audio RCA Output
- 3 Left Analog Unbalanced Audio RCA Output
- 4 5VDC / 1A 2.5mm DC Power Input Jack

SAFETY PRECAUTIONS

1. To prevent fire or shock hazard, do not expose this equipment to high humidity and/or dust. Do not use in an unprotected outdoor installation nor any area classified as overly damp or wet.
2. The temperature for installation should be kept between 32°F to 140°F (0°C to 60°C). Avoid direct sunlight exposure or extreme changes of temperature over a short period of time.
3. Do not disassemble the unit as this voids the warranty.
4. Do not drop the unit and avoid heavy impact.
5. This unit should not be permanently installed unless proper ventilation is provided. Any enclosure openings must not be blocked or covered as they protect the unit from overheating.
6. Before cleaning, turn off the power and unplug the unit from all connections. Use a damp cloth. Do not use liquid or aerosol cleaners.
7. Do not overload outlets and extension cords as this may result in a risk of fire or electric shock.
8. Enclosure entry is dangerous. Never push objects of any kind, including liquids, into this unit through openings as they may touch dangerous voltage points or short-out parts that could result in a fire or electric shock.
9. Do not attempt to open or service this unit yourself as opening or removing covers may expose you to dangerous voltage and other hazards.
10. There are no user-serviceable parts inside the unit. If the unit requires service contact your authorized dealer, or an authorized repair service company.

Federal Communications Commission (FCC) Compliance Notices

Class A Interference Statement

This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.

FCC Caution

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

SESCOM

PO Box 720 • Mt. Marion, NY 12456 • USA

845.246.1915 • sales@sescom.com