

SES-3MIX Datasheet

DESCRIPTION:

The SES-3MIX is a plug and play unit that mixes 3 XLR or 1/4 inch TRS inputs into 1 XLR or 1/4 inch TRS output, perfect for inputting additional equipment into mixers with limited inputs. Each 1/4 inch/XLR combo channel features a dedicated potentiometer for level adjustment. Intended for use with mic or line-level, balanced or unbalanced signals. Fully passive, no batteries or AC power needed.

Sescom Tech Note: Not intended for use with high-impedance signals.

FEATURES:

- Easy to Use 3 Channel Line Mixer & Mic Mixer
- High quality locking 1/4 inch/XLR combo connectors
- Passive design requires no power
- Independent level/volume control for each channel
- Rugged black anodized aluminum enclosure

SPECIFICATIONS:

- **Input Connectors:** (3) Neutrik 1/4 inch TRS Jack/XLR Female Combo
- **Output Connectors:** (1) Neutrik XLR male, (1) 1/4 inch TRS Jack
- **Dimensions:** 5.25" x 3.25" x 2.75"
- **Weight:** 11.8 oz
- **Impedance (Ohms):**
 - Unbalanced: 1.25K to 10K
 - Balanced: 2.5K to 20K

