

SES-3MIX-HZ Datasheet

DESCRIPTION:

The SES-3MIX-HZ is a plug-and-play unit that combines 3 ¼-inch TRS inputs into Left/Right RCA outputs or a ¼-inch TRS output, making it ideal for integrating additional equipment into mixers with limited inputs. Each ¼ inch TRS channel features a dedicated potentiometer for level adjustment. Intended for use with instrument-level signals, balanced or unbalanced signals. Entirely passive, no batteries or AC power needed.

Sescom Tech Note: When using a TRS signal, if using unbalanced signals, all signals must be unbalanced; if using balanced signals, all signals must be balanced. Do not mix balanced and unbalanced signals. The SES-3MIX-HZ is not compatible with phantom power.

FEATURES:

- Easy to Use 3 Channel Instrument-Level Mixer
- High-quality 1/4-inch TRS/TS Inputs
- Left/Right RCA and ¼-inch TRS Outputs
- Passive design requires no power
- Independent level/volume control for each channel
- Rugged black anodized aluminum enclosure

SPECIFICATIONS:

- **Input Connectors:** (3) ¼-inch TRS Jack
- **Output Connectors:** (2) RCA (White/Red) Jacks, (1) ¼-inch TRS Jack
- **Dimensions:** 5.25" X 3.25" X 2.75"
- **Weight:** 11.8 oz
- **Impedance (Ohms):**
 - **Unbalanced:** 12.5K to 100K
 - **Balanced:** 25K to 200K

