

## SES-MKP-41 Datasheet

### DESCRIPTION:

The Sescom SES-MKP-41 is a compact passive inline audio level controller designed to attenuate microphone-level signals. Engineered for audio professionals and enthusiasts alike, this device provides effortless level control between your microphone and preamp or mixing console—no power supply required, no added noise floor—just clean, immediate attenuation right at the source.

**Sescom Tech Note:** Intended for use with microphone-level signals. Not compatible with phantom power.

### FEATURES:

- Microphone level impedance
- Rugged, Compact, Black-Anodized Aluminum Enclosure
- Optimized for Microphones
- Easy Plug and Play Setup
- High-Quality Neutrik 3-Pin XLR Connectors

### SPECIFICATIONS:

- **Dimensions:** 3" x 3" x 1.25"
- **Input Impedance (Ohms):** 1K
- **Input:** 3-Pin XLR
- **Output:** 3-Pin XLR

